

DSP VLSI Systems

Homework (IX)

Processing Elements Design

Deadline: You don't need to deliver this homework.

1. Find the simplest implementation of a serial/parallel multiplier with fixed coefficient when the coefficient is

(a) $(0.011001)_{2C}$

(b) $(0.111011)_{2C}$

(c) $(1.011001)_{2C}$

2. Conversion between RGB and YCbCr digital color video image formats can be performed by the following transformations:

$$R = Y + 350Cr / 256 - 175 / 256$$

$$G = Y - 86Cb / 256 - 178Cr / 256 + 132 / 256$$

$$B = Y + 444Cb / 256 - 222 / 256$$

and

$$Y = (77R + 150G + 29B) / 256$$

$$Cb = (-44R - 87G + 131B) / 256 + 128$$

$$Cr = (131R - 110G - 21B) / 256 + 128$$

The color components are quantized to 8 bits. Derive an implementation based on

(a) Bit-serial multipliers

(b) Distributed arithmetic

(c) Compare the two implementations.

3. Describe how to use CORDIC to efficiently compute the distance of a point (x, y) to the origin.